1 2

5

Original Research Article

Theoretical Computation of Magnetic Field Density within the Vicinity of Rukpokwu 11 KVA Distribution Power Lines

Abstract

6 In this study, we calculated the magnetic field exposure from extremely low frequency magnetic field around 11 7 kVA power distribution lines at Rukpokwu, Rivers State, Nigeria using theoretical and mathematical 8 formulations. 32 sample points were considered at horizontal distances of between 1m and 1000m from the foot 9 of the vertical pole subtending the electrical conductors. We used a mathematical software (Wolfram 10 Mathematica 8.0) to generate the initial results of the magnetic field current coefficients (I_{coef}) for the vertical 11 and horizontal components of the magnetic fields and the total magnetic fields for x=1 to 1000 m (horizontal distance from the foot of the pole) for a vertical height of 1 m above the ground surface (considered to be the 12 13 average height of head positions of the workers and the public within the vicinity of magnetic field). The results 14 showed that for horizontal distances of between 1 and 10m, the magnetic field exposures ranged from 15 $45.82 \,\mu$ T/hr to $21.62 \,\mu$ T/hr and are above the occupational field exposure limit of $21.0 \,\mu$ T/hr set by 16 International Committee on Non Ionizing Radiation Protection (ICNRIP). Also, the results of field exposure for 17 horizontal distances ranging from 1 to 20m were between $45.82 \,\mu T/hr$ and $8.3 \,\mu T/hr$ and are above the 18 ICNRIP limit of $4.2 \,\mu T/hr$ set for the public. It is suggested that between horizontal distances of 1 and 10m 19 from the distribution lines, it is unsafe to build shops and do businesses and between the horizontal distances of 20 1 to 20m it is unsafe to build residential areas.

21

22 1. Introduction

When charges move, current flow is induced, consequently magnetic fields are created around the vicinity of the conductor where the current is flowing. Most high voltage power lines in Nigeria consist of vertically positioned brick cylindrical poles with 3 horizontally separated metallic conductors drawn on these poles which act as pathways for current. The current that flows across these horizontal conductors generate magnetic field. In the absence of a well calibrated magnetometer, theoretical estimation of the magnitude of the magnetic field intensity around these power lines is possible and recommendable.

In recent years, due to technology and massive industrialization, and consequently greater need for power generation, electric power lines crisscross our cities, urban areas and the rural areas giving rise to extremely low magnetic fields in our environment.

32

33 Electric and magnetic fields are present around all wires carrying electricity, high voltage power lines, house 34 wiring, or wires inside domestic appliances. The strength of the electric field depends on the voltage, while the 35 strength of the magnetic field depends on the size of the current carried. [1] Low frequency electromagnetic 36 field around electrical power substations is quasistatic with two component vector fields; the electric field 37 caused by charges and eddy component of the magnetic field caused by currents. Calculation of field intensity 38 of these fields at points away from the source (charges and currents) can be computed with thin-wired 39 approximation. [2] Previous researchers had carried out theoretical calculations and experimental measurements 40 of exposure of children living close to a major transmission line in Norway. The results revealed that children 41 living close to a major transmission line had a greater exposure to magnetic fields than children living farther 42 away. A fairly good correlation was also seen between measured and calculated exposure. [3] Exposure to 43 magnetic fields was measured around the vicinity of 34.5 KV power distribution lines. The results were 0.2 to 44 $2.7 \,\mu\text{T}$, 0.1 to 0.5 μT and 0.1 to 0.2 μT at 0 ft, 50 ft and 100 ft respectively from the wire lines. [4] 45 Computation of the magnetic field from the three phase 63 kV power transmission lines has been carried out by

46 previous researchers using a new magnetic field simulation package- Marvdasht. The results of this study

47 confirmed the environmental pollution of the magnetic field produced near transmission lines. By using the

48 curves of magnetic field around the 63kV transmission lines obtained from software, they were able to

49 determine the safe distance around the towers. [5] Studies on the effect of electromagnetic radiation emitted

from 400KV high voltage transmission lines on human health were carried out. The results ranged between 1.8 to $7.6 \,\mu$ T and were in close agreement with measured values. [6]

52 In Nigeria, many persons are living and doing businesses under the transmission lines and are constantly 53 exposed to the ELF electromagnetic fields. ELF measuring meters are not always available and even the 54 available ones may not be routinely calibrated. In this work, we have adopted the basic Physics laws in 55 calculating the magnetic field around 11 kV distribution lines to ascertain the prevailing magnetic field exposure 56 of individuals who live and work around the power lines.

57

58 2. Methodology

59 2.1 Study Area

60 This study was carried out in Rukpokwu, Rivers State, Nigeria. This area is one of the emerging cities within the

61 New Greater Port Harcourt Area of Rivers State with a very high population density and has become a be-hive

62 of business and commercial activities. The area has a network of power distribution and transmission cables of

63 power lines from both the national grid and the state power supplies. Many business activities and living houses

- are within the vicinity of 11 kVA power lines. Figure 1 shows the picture of people doing businesses under the
- 65 power lines.

66



- 67 68
 - 8 Figure 1. People doing business under 11 kVA power lines along Rukpokwu, Nigeria
- 69 2.2. Theoretical Formulations and Computations

70 Our theory was based on the Ampere's law; $\oint Bdl = \mu_o t$

(1)

71 Where the line integral is over any arbitrary loop, I is the current enclosed by the loop and μ_0 is the permeability 72 constant for free space.

73

The magnetic field generated by 11 kV distribution line was calculated at 1m above the ground. The wires wereassumed to be perfectly arranged horizontally.

76 Let the average conductor height (from the ground level) be 10.37 m and the distance of separation between the 77 two external wires (conductors) from the central wire be designated z (0.17m). Let the magnetic field (B) for 78 one conductor be perpendicular to the radius of its circular magnetic field lines. Let this magnetic field vector be 79 resolved into the horizontal components, and vertical components. The positions of the observation point and 80 that of the wire are described using XY coordinates. This is illustrated in Figure 2.

- 81
- 82 83
- 84
- 85
- 86



- 131 In computing the magnetic field components produced by the current i_a and i_b for the two external wires, the
- 132 geometry is the same as the magnetic field components produced by i with x component replaced by (x z) and
- 133 (x + z) for i_a and i_b respectively. Thus, for external wire carrying i_a , the two field components are;

134
$$\mathbf{B}_{xa} = -\frac{i_a \mu_o y}{2\pi \{(x-z)^2 + y^2\}}$$
(8)

135
$$\mathbf{B}_{ya} = \frac{\iota_a \mu_o (\mathbf{x} - \mathbf{z})}{2\pi \{ (\mathbf{x} - \mathbf{z})^2 + \mathbf{y}^2 \}}$$
(9)

136 Similarly, for external wire carrying i_b, the two field components are;

137
$$\mathbf{B_{xb}} = -\frac{i_b \mu_o y}{2\pi \{(x+z)^2 + y^2\}}$$
(10)

138
$$\mathbf{B_{yb}} = \frac{i_a \mu_o (\mathbf{x} + \mathbf{z})}{2\pi \{ (\mathbf{x} + \mathbf{z})^2 + \mathbf{y}^2 \}}$$
(11)

Note that we shall be referring to the coefficients of the current terms in equations (6) to (11) as currentcoefficient terms for the respective magnetic field components.

141

In order to transform the 3 phase currents (i, i_a and i_b) into a single RMS current I, we took cognizance of the fact that the 3 phase systems produce magnetic fields that rotate in specified directions. These 3 phase wires carrying alternating current of same frequency reach their instantaneous peak values such that i_a leads i by 120° and i_b lags i by 120° [5]. These are represented in the phase diagram of Figure 4.

- 146
 Therefore, $i = I \sin wt$ (12)

 147
 $i_a = I \sin (wt + 120^{\circ})$ (13)
- 148 $i_{\rm b} = I \sin ({\rm wt} 120^{\circ})$ (14)
- 149 Considering Figure 3 and resolving the currents in phase and out of phase in terms of current I, we have the 150 results in Table 1.





162 Figure 4: Resolution of the 3- phase currents into a single RMS current, I

163

- 165
- 166
- 167

168

169 in Table 1 are referred to as current factors). 170 171 I_b Ia Phase currents i 172 173 I-in - ½I = -9.57 A I = 19.13- ½I = -9.57 A $-\frac{\sqrt{3}}{2}I = -9.57 \text{ A}$ $\frac{\sqrt{3}}{2}I = 16.57$ A 174 I-out 0 175 176 177 From Table 1 above, we can determine for each current, the in-phase vertical, out of phase vertical, in-phase 178 horizontal and the out of phase horizontal components of magnetic field by multiplying magnetic field current 179 coefficients by the appropriate current factors. 180 Therefore the three-out-of phase vertical components of magnetic field for each of the three currents (i, i_a and i_b) 181 will be computed using the current factors in Table 1; For i, $B_y \text{ out} = \frac{0\mu_0 x}{2\pi(x^2 + y^2)} = 0$ 182 (15)183 Doing the same for I_a and I_b ; \mathbf{B}_{ya} out = $\frac{16.57 \,\mu_0(x-z)}{2\pi \{(x-z)^2 + y^2\}}$ 184 (16) $\mathbf{B}_{\mathbf{yb}} \text{ out} = \frac{-16.57\mu_0(\mathbf{x}+\mathbf{z})}{2\pi\{(\mathbf{x}+\mathbf{z})^2 + \mathbf{v}^2\}}$ 185 (17)186 Therefore total B_v-out will be given as; B_y out-T = $\frac{16.57 \,\mu_0}{2\pi} \left\{ \frac{(x-z)}{\{(x-z)^2 + y^2\}} - \frac{(x+z)}{\{(x+z)^2 + y^2\}} \right\}$ 187 (18)188 189 The three in- phase vertical components for each of the three current (i, i_a and i_b) were computed using similar 190 procedure and adopting the current factors in Table 1; 191 Therefore total B_v in- phase will be given as; $B_{y} \text{ in-}T = \frac{-9.57 \,\mu_{0}}{2\pi} \{ \frac{(x-z)}{\{(x-z)^{2}+y^{2}\}} + \frac{(x+z)}{\{(x+z)^{2}+y^{2}\}} \} + \frac{19.3 \,\mu_{0}x}{2\pi(x^{2}+y^{2})} \}$ 192 (19)193 Similarly, total B_x out of phase will be given as; 194 B_x out-T = $-\frac{16.57\mu_0 y}{2\pi\{(x-z)^2+y^2\}} + \frac{16.57\mu_0 y}{2\pi\{(x+z)^2+y^2\}}$ 195 (20)196 197 Also, total B_x in- phase will be given as; $B_{x} \text{ in-T} = \frac{9.57 \,\mu_{0}}{2\pi} \left\{ \frac{y}{\{(x-z)^{2}+y^{2}\}} + \frac{y}{\{(x+z)^{2}+y^{2}\}} \right\} - \frac{19.13 \,\mu_{0}x}{2\pi(x^{2}+y^{2})}$ 198 (21)199 200 The square of the grand sum of all the component magnetic fields both in- phase and out of phase is the sum of 201 the squares of equations (18) to (21); $\mathbf{B}_{T}^{2} = \mathbf{B}_{v}^{2} \text{ out-} T + \mathbf{B}_{v}^{2} \text{ in-} T + \mathbf{B}_{x}^{2} \text{ out-} T + \mathbf{B}_{x}^{2} \text{ in-} T$ 202 (22)

Table 1. In-phase and out of phase current in terms of RMS current, I = 19.13 A (the values of current

203 Hence,
$$\mathbf{B}_{\mathrm{T}} = (B_{\mathrm{y}}^{2} \text{out} - \mathrm{T} + B_{\mathrm{y}}^{2} \text{in} - \mathrm{T} + B_{\mathrm{x}}^{2} \text{out} - \mathrm{T} + B_{\mathrm{x}}^{2} \text{in} - \mathrm{T})^{1/2}$$
 (23)

204

205 We went further to adopt a mathematical software (Wolfram Mathematica 8.0) which enabled us facilitate the 206 generation of the results of the magnetic field current coefficients (I_{coef}) for the vertical and horizontal 207 components of the magnetic fields (both in-phase an out of phase) for x=1m to 1000 m (horizontal distance 208 from the foot of the pole) for a vertical height of 1 m above the ground surface (presumed to be the average 209 height of head positions of those who live and do business within the vicinity of the understudied magnetic 210 field). This software also enabled us to calculate the total magnetic field for x=1m to 1000 m. In carrying out 211 these computations, we used the parameters collected from Power Holdings Company of Nigeria (PHCN). 212 These parameters include; Power = 11 kVA, Line voltage = 415V, Height of pole = 10.37m, Distance between 213 central horizontal conductor and the two external horizontal conductors 'z' = 0.17m. The current in the 214 horizontal conductor 'I', was calculated using the Expression;

215

216
$$I = \frac{Power}{v\cos\theta\sqrt{3}} = 19.13 \text{ A}$$
 (24)

217 (Where Power = $VI \cos \theta \times \sqrt{3}$ and $\cos \theta$ (power factor) = 0.8)

218

219 **3. Results**

220 The results of the magnetic field current coefficients (I_{coef}) for the vertical and horizontal components of the 221 magnetic fields (both in-phase an out of phase) for x=1m (horizontal distance from the foot of the 222 pole) for a vertical height of 1 m above the ground surface are presented in Table 2. Summary of the results 223 of the component magnetic fields for the various phases and their corresponding total magnetic fields are 224 presented in Table 3. The results of the computed total magnetic field exposure are presented in Table 4. We 225 have assumed that the computed magnetic fields are generated per second, therefore all the results are expressed 226 as magnetic field exposure in Tesla per second (T/s). In order to convert from μ T/sec to μ T/hr we have used;

227 1
$$\mu$$
T/hr = μ T/sec x 3600

We presented the relationship between magnetic field exposures in μ T/hr against the corresponding horizontal distances in meters in Figure 5. A comparison between the results of the calculated magnetic field exposure in μ T/hr and the standard limits established by International Committee on Non Ionizing Radiation Protection (ICNRIP) has been presented in Table 5. We assumed occupational and public exposure limits of 500 μ T/day and 100 μ T/day respectively as set by ICNRIP 1998 guidelines [7] which we computed to be approximately

equal to 21 μ T/hr and 4.2 μ T/hr for occupational and public exposure limits respectively.



236

B- Phase	Current	A	В	С	Icoef.	Ι	Magnetic Field Icoef. * I
	Ib	x+y	x+y	у	2.00E-10	-16.57	-3.31E-09
By. Out	i	Х	Х	у	2.00E-10	0	0
	Ia	X-Z	X-Z	у	2.00E-10	16.57	3.31 E-09
	Ib	x+y	x+y	у	2.00E-10	-9.57	-1.91E-09
By. In	i	Х	Х	у	2.00E-10	19.13	3.83E-09
	Ia	X-Z	X-Z	у	2.00E-10	-9.57	-1.91416E-09
	Ib	Y	x+z	у	1.87E-12	-16.57	-3.10389E-11
B _x . Out	i	Y	Х	у	1.87E-12	0	0

(25)

	Ia	Y	X-Z	у	1.87E-12	16.57	3.11E-11
	Ib	Y	x+z	у	1.87E-12	-9.57	-1.79265E-11
Bx. In	i	Y	х	у	1.87E-12	19.13	3.58E-11
	Ia	Y	X-Z	у	1.87E-12	-9.57	-1.79387E-11

Table 3. Summary of the total magnetic field for the different phases and the total magnetic fields for X = 1 m to
 1000 m

S/n	X (m)	By Out _T	By In _T	B xOut _T	Bxin _T	B ² _T	B _T (Tesla)
1	1	-1.20E-08	1.00E-09	4.00E-09	1.00E-09	1.62E-16	1.26853E-08
2	2	-1.12E-08	-2.74E-11	4.32E-09	-6.35E-10	1.45E-16	1.20218E-08
3	5	-5.60E-09	5.00E-10	8.30E-09	-1.56E-09	1.03E-16	1.01456E-08
4	10	3.89E-10	-7.90E-11	5.99E-09	-1.33E-10	3.61E-17	6.00461E-09
5	15	1.58E-09	-9.35E-11	3.24E-09	-7.97E-11	1.30E-17	3.60681E-09
6	20	1.48E-09	-8.42E-11	1.775E-09	-4.84E-11	5.35E-18	2.31311E-09
7	30	9.38E-10	-6.29E-11	6.492E-10	-2.23E-11	1.31E-18	1.1427E-09
8	40	5.982E-10	-4.87E-11	2.965E-10	-1.21E-11	4.48E-19	6.69532E-10
9	50	4.059E-10	-3.93E-11	1.577E-10	-8.02E-12	1.91E-19	4.37302E-10
10	60	2.909E-10	-3.30E-11	9.316E-11	-5.3E-12	9.44E-20	3.07276E-10
11	70	2.179E-10	-2.84E-11	5.941E-11	-3.88E-12	5.18E-20	2.27665E-10
12	80	1.69E-10	-2.48E-11	4.013E-11	-2.96E-12	3.08E-20	1.75486E-10
13	90	1.346E-10	-2.21E-11	2.835E-11	-2.33E-12	1.94E-20	1.39337E-10
14	100	1.097E-10	-2E-11	2.075E-11	-1.89E-12	1.29E-20	1.13438E-10
15	110	9.11E-11	-1.81E-11	1.56E-11	1.55E-12	8.87E-21	9.41944E-11
16	120	7.69E-11	-1.67E-11	1.20E-11	-1.31E-12	6.34E-21	7.96114E-11
17	130	6.52E-11	-1.54E-11	9.52E-12	-1.11E-12	4.58E-21	6.76762E-11
18	140	5.68E-11	-1.43E-11	7.63E-12	-9.55E-13	3.49E-21	5.9075E-11
19	150	4.95E-11	-1.33E-11	6.21E-12	-8.39E-13	2.67E-21	5.16373E-11
20	160	4.36E-11	-1.24E-11	5.03E-12	-7.33E-13	2.08E-21	4.56131E-11
21	170	3.86E-11	-1.18E-11	4.27E-12	-6.55E-11	5.94E-21	7.70564E-11
22	180	3.45E-11	-1.12E-11	3.60E-12	-5.80E-13	1.33E-21	3.64554E-11
23	190	3.10E-11	-1.58E-11	3.06E-12	-5.25E-13	1.22E-21	3.49321E-11
24	200	2.80E-11	-1.01E-11	2.63E-12	-4.69E-13	8.93E-22	2.98854E-11
25	300	4.10E-12	-2.22E-12	7.72E-13	-2.09E-13	2.24E-23	4.73055E-12
26	400	6.06E-12	-5.76E-12	2.95E-13	-1.54E-13	7.00E-23	8.36731E-12
27	500	3.58E-12	-4.02E-12	1.19E-13	-1.23E-13	2.90E-23	5.38573E-12
<mark>28</mark>	<mark>600</mark>	3.08E-12	-1.11E-12	<mark>9.79E-14</mark>	<mark>-9.96E-11</mark>	9.93E-21	9.96638E-11
29	700	2.30E-12	-2.85E-12	6.15E-14	-3.82E-14	1.34E-23	3.66302E-12
30	800	5.87E-13	-2.50E-12	4.12E-14	-2.93E-14	6.60E-24	2.56849E-12

31	900	1.37E-12	-2.27E-12	2.90E-14	-2.31E-14	7.03E-24	2.65164E-12
32	1000	1.12E-12	-2.01E-12	2.11E-14	-1.87E-14	5.30E-24	2.30115E-12

Table 4: The Rate of Magnetic Field Exposures for Specified Horizontal
Distances from the Central Conductor

S/n	HORIZONTAL DISTANCE (X, m)	Field Exposure T/sec	Field Exposure uT/sec	Field Exposure uT/hr
1	1	1.27E-08	1.27E-02	45.82
2	2	1.20218E-08	1.20E-02	43.28
3	5	1.01456E-08	1.01E-02	36.52
4	10	6.00461E-09	6.00E-03	21.62
5	15	3.60681E-09	3.61E-03	12.98
6	20	2.31311E-09	2.31E-03	8.33
7	30	1.1427E-09	1.14E-03	4.11
8	40	6.69532E-10	6.70E-04	2.41
9	50	4.37302E-10	4.37E-04	1.57
10	60	3.07E-10	3.07E-04	1.11
11	70	2.28E-10	2.28E-04	0.82
12	80	1.75486E-10	1.75E-04	0.63
13	90	1.39337E-10	1.39E-04	0.50
14	100	1.13438E-10	1.13E-04	0.41
15	110	9.41944E-11	9.42E-05	0.34
16	120	7.96114E-11	7.96E-05	0.29
17	130	6.76762E-11	6.77E-05	0.24
18	140	5.9075E-11	5.91E-05	0.21
19	150	5.16373E-11	5.16E-05	0.19
20	160	4.56131E-11	4.56E-05	0.16
21	170	7.70564E-11	7.71E-05	0.28
22	180	3.64554E-11	3.65E-05	0.13
23	190	3.49321E-11	3.49E-05	0.13
24	200	2.98854E-11	2.99E-05	0.11
25	300	4.73055E-12	4.73E-06	0.02
26	400	8.36731E-12	8.37E-06	0.03
27	500	5.38573E-12	5.39E-06	0.02
<mark>28</mark>	600	9.96638E-11	9.97E-05	0.36
29	700	3.66302E-12	3.66E-06	0.01
30	800	2.56849E-12	2.57E-06	0.01
31	900	2.65164E-12	2.65E-06	0.01
32	1000	2.30115E-12	2.30E-06	0.01

246



Figure 5: Relationship between magnetic field exposure and the horizontal distance away from the conductor

249

Table 5: Comparison of Magnetic field exposure in micro Tesla per hour (µT/hr) with the international
 standard limits.

		ICNRIP LIMIT			
s/n	HORIZONTAL DISTANCE		PUBLIC	Occupational	
	X (m)	µT/hr	µT/hr	μ1/hr	
1	1	45.82	4.2	21	
2	2	43.28	4.2	21	
3	5	36.52	4.2	21	
4	10	21.62	4.2	21	
5	15	12.98	4.2	21	
6	20	8.33	4.2	21	
7	30	4.11	4.2	21	
8	40	2.41	4.2	21	
9	50	1.57	4.2	21	
10	60	1.11	4.2	21	
11	70	0.82	4.2	21	
12	80	0.63	4.2	21	

13	90	0.50	4.2	21
14	100	0.41	4.2	21
15	110	0.34	4.2	21
16	120	0.29	4.2	21
17	130	0.24	4.2	21
18	140	0.21	4.2	21
19	150	0.19	4.2	21
20	160	0.16	4.2	21
21	170	0.28	4.2	21
22	180	0.13	4.2	21
23	190	0.13	4.2	21
24	200	0.11	4.2	21
25	300	0.02	4.2	21
26	400	0.03	4.2	21
27	500	0.02	4.2	21
28	600	0.36	4.2	21
29	700	0.01	4.2	21
30	800	0.01	4.2	21
31	900	0.01	4.2	21
32	1000	0.01	4.2	21
252				

253 4. Discussions

The results of the the magnetic field current coefficients (I_{coef}) for the vertical and horizontal components of the magnetic fields (both in-phase and out of phase) for x=1m have been successfully computed using Wolfram Mathematica 8.0 software and have been presented in Table 2. The product of I_{coef} and I for each of the phases enabled us to compute the magnetic fields in Tesla. On application of Wolfram Mathematica 8.0 software, inputting x = 1m to 1000 m, the equivalent magnetic fields in Tesla were generated automatically. This application software helped us to overcome the rigours of computing each of the magnetic fields manually for the numerous horizontal distances (x = 1m to 1000 m) from the conductors considered in this work.

261

262Table 3 presents the summary of the total magnetic field for the different phases and the total magnetic fields for263 $X = 1 \text{ m to } 1000 \text{ m as computed using Wolfram Mathematica 8.0 software. The results ranged from 1.26853E-08264to 2.30115E-12 Tesla for x = 1 m to x = 1000 m respectively, implying a decline in the magnitude of total265magnetic field with respect to increase in horizontal distances away from the foot of the pole.$

266 In Table 4, the results of the rate of magnetic field exposures presented for the various horizontal distances from 267 the central conductor (x = 1m to x = 1000 m) ranged from 45.8µT/hr to 0.01µT/hr. For x = 1 to 20 m, the 268 magnetic field exposure exceeded the standard limits of 4.2 µT/hr and 21 µT/hr set by ICNIRP for both public 269 and occupational areas respectively [7]. These values suggest that within the horizontal distances of between 1

to 20 m, people should not build residential houses. Within the range of 1 to 10 m, we have values above the

standard limit of 21.0μ T/hr set by ICNIRP (1998) for the occupational area [7]. Also, these values suggest that

people should not do business close to the power lines to avoid undue exposure to magnetic fields.

From the results, the horizontal distances of x=30m to x=1000m have magnetic field exposures below the standard limits set by ICNIRP. It follows that within these horizontal distances, it is safe for people to reside and also do their businesses.

Figure 5 shows a decrease in the magnetic field exposure as the horizontal distances from the conductor increase. This fact is demonstrated in the exponential decay curve of the magnetic field exposure against the horizontal distances. It shows that at horizontal distances well above x = 200m, the magnetic field exposure remains relatively uniform as the horizontal distances increased. This indicates that the magnetic field exposures within these horizontal distances are too small to have any significant impact or changes on the public and occupationally exposed persons. In a similar work done by Adnan using 400 kVA high voltage power lines, he

282 computed a range of magnetic field exposure values of between 7.6μ T/hr and 1.8μ T/hr while the measured 283 values ranged from 7.36μ T/hr to 1.7μ T/hr respectively. He showed from these results that the calculated values 284 agreed with the measured values. The results of the present research fall within this range [6].

285 5. Conclusion

286 In this research, we have calculated the magnetic field exposure from extremely low frequency magnetic field around 11 kVA power distribution lines at Rukpokwu, Rivers State, 287 288 Nigeria using theoretical and mathematical formulations. The results showed that for 289 horizontal distances of between 1 and 10m, the magnetic field exposures ranged from 290 $45.82 \,\mu$ T/hr to $21.62 \,\mu$ T/hr and are above the occupational field exposure limit of $21.0 \,\mu$ T/hr 291 set by International Committee on Non Ionizing Radiation Protection (ICNRIP). Also, the 292 results of field exposure for horizontal distances ranging from 1 to 20m were between 293 $45.82 \,\mu T/hr$ and $8.3 \,\mu T/hr$ and are above the **ICNRIP** limit of $4.2 \,\mu T/hr$ set for the public. 294 It is suggested that between horizontal distances of 1 and 10m from the distribution lines, it is 295 unsafe to build shops and do businesses and between the horizontal distances of 1 to 20m it is 296 unsafe to build residential areas.

297

298 Reference

[1] National Radiation Laboratory, 2008. Ministry of Health, 108 Victoria Street, Christchurch, New Zealand

- **300** (03) 366 5059, www.nrl.moh.govt.nz
- 301

302 [2] Hidajet Salkic, Amir Softic, Adnan Muharemovic, Irfan Turkovic and Mario Klaric (2012). Calculation and

303 Measurement of Electromagnetic Fields, Electromagnetic Radiation, Prof. S. O. Bashir (Ed.), ISBN: 978-95351-

304 0639-5, InTech, Available from: <u>http://www.intechopen.com/books/electromagnetic-radiation/calculationand-</u>
 305 <u>measurement-of-electromagnetic-fields</u>

306 [3] A. I. Vistnes, G. B. Ramberg, L. R. Bjørnevik, T. Tynes and T. Haldorsen. Exposure of Children to Residential
 307 Magnetic Fields in Norway, Bioelectromagnetics 18:47–57, 1997.

308 [4] Long Island Power Authority, Magnetic Field, 2013. Magnetic Field Levels around Homes. Retrieved on
 309 14/06/2016 from www.saunasandstuff.com

[5] Mehdi, N., Ghahraman, S and Masoud J, MAGNETIC FIELD CALCULATION OF 63KV TRANSMISSION LINES,
 IJRRAS 17 (2), November 2013, <u>www.arpapress.com</u>

[6] Adnan, M.K., 2013. Investigation and Study the Effect of Electromagnetic Radiation Emitted from 400KV
High Voltage Transmission Lines on Human Health. Tikrit Journal of Pure Science, 18 (3) 135-137

314 [7] National Radiation Laboratory, 2008. Electrical and Magnetic Fields and Your Health, Ministry of Health,

315 108 Victoria Street, Christchurch, New Zealand, Retrieved on 10/10/2016 from www.nrl.moh.govt.nz