| 1 | Original Research Article | |
|--------|--|--|
| 2 | Controllable rogue waves | |
| 3 | in the generalized nonlinear Schrödinger equations | |
| 4 | | |
| 5 | | |
| 6 7 | Abstract: We obtain the rogue waves with a controllable center in the generalized | |
| 8 | nonlinear Schrödinger equation by using a direct method. The position of these solutions can | |
| 9 | be controlled by varying different center parameters. We study the effects of different | |
| 10 | parameters on rogue waves and hence find that the nonlinearity parameter is responsible for | |
| 11 | the width of rogue waves. With the increase of the nonlinearity parameter, the rogue wave | |
| 12 | becomes wider. What is more, the negative nonlinearity parameter can yield some singular | |
| 13 | rogue waves. | |
| 14 | Keywords: Generalized nonlinear Schrödinger equation; Rogue wave; Singular rogue wave | |
| 15 | 1. Introduction | |
| 16 | Rogue waves, are called freak waves, monster waves, killer waves, giant waves or | |
| 17 | extreme waves, Rogue waves are spontaneous nonlinear waves with amplitudes significantly | |
| 18 | larger (two or more times higher) than the surrounding average wave crests [1,2], What is | |
| 19 | more, they appear from nowhere and disappear without a trace. | |
| 20 | It is a very meaningful work to search for rogue waves, which has been found in many | |
| 21 | different systems and has many important applications in some fields since they can signal | |
| 22 | fascinating stories [3,4]. | |
| 23 | In this paper, we study the generalized nonlinear cubic Schrödinger equation | |
| 24 | $i\frac{\partial\psi}{\partial x} + A\frac{\partial^2\psi}{\partial t^2} + \psi \psi ^2 = 0, \qquad (1)$ | |
| 25 | where x is the propagation distance and t is the transverse variable. When A=0, equation (1) | |
| 26 | becomes the famous nonlinear cubic Schrödinger equation. Some rogue wave solutions of the | |
| 27 | | |
| 28 | nonlinear cubic Schrödinger equation have been found by taking limit of Akhmediev breather | |

29 solutions[5,6] and Darboux transformation.[7,8]. By a similarity transformation, rogue wave 30 solutions to the generalized nonlinear Schrodinger equation with variable coefficients are obtained [9]. 31 Using the $(\text{Exp}(-\phi(\xi)))$ -Expansion method, some new exact traveling wave solutions of the cubic 32 nonlinear Schrodinger equation are given [10]. The center of these solutions is located at a fixed 33 point (0, 0) on (x, t) plane. Basing on a simple assumption, WANG et al. [11] founded larger 34 universality and applicability of rogue waves with a controllable center. The above method 35 does not consider the effect of parameters on the waveform, which is our interest. More 36 researches on rogue waves can be founded in Ref. [12-21].

37 In this paper, our interests focus on two aspects:

(1) We want to determine rogue wave solutions of Eq. (1) with an arbitrary coefficient ofnonlinearity;

40 (2) We want to know the role of the nonlinearity coefficient on the formation of rogue waves.
41 The organization of this paper is as follows. In Section 2, we obtain some special rogue
42 waves with a controllable center by a direct method. In Section 3, we analyze the different
43 controllability by numerical simulation. Conclusion will be given.

44 **2. Some special rogue waves**

45 By the similar method in Ref. [9], we assume rogue waves as follows

$$\Psi_1 = \left(1 + \frac{p_1 + iq_1}{h_1}\right)e^{ix} \tag{2}$$

47 with

46

48

$$p_1(x,t) = a_0 + a_1 x + a_2 t, \tag{3}$$

49
$$q_1(x,t) = b_0 + b_1 x + b_2 t,$$
 (4)

50
$$h_1(x,t) = c_1(x-\alpha)^2 + c_2(t-\beta)^2 + c_3.$$
 (5)

51 Here α_i , b_i (i = 0, 1, 2), c_j (j = 1, 2, 3), α , β are real parameters.

52

Substituting the function ψ_1 into Eq. (1) and setting different coefficient Lists to be zero. We obtain the following possible system of nonlinear algebraic equations with the aid of Maple.

$$-3b_2c_1^2 = 0,$$

57
$$-3b_2c_2^2 = 0$$
,

58
$$2a_2b_2c_2 + a_1c_2^2 = 0,$$

59
$$8\alpha a_2 c_1 c_2 - 2b_2 c_1 c_2 - 6\alpha^2 b_2 c_1 c_2 - 16\beta a_1 c_2^2 + 12\beta b_0 c_2^2 - 18\beta^2 b_2 c_2^2 - 6b_2 c_2 c_3 = 0, \quad (6)$$

$$60 \qquad -6a_0c_1c_2 + 12\alpha a_1c_1c_2 + 12\beta a_2c_1c_2 - 54\alpha^2 c_1^2 c_2 - 54\beta^2 c_1c_2^2 - 18c_1c_2c_3 = 0,$$

$$-6a_1c_1c_2 + 36\alpha c_1^2c_2 = 0,$$

62
$$4a_1c_2^2 - 3b_0c_2^2 + 12\beta b_2c_2^2 = 0,$$

63
$$12\alpha a_2c_1c_2 + 8b_2c_1c_2 + 12\beta a_1c_2^2 - 72\alpha\beta c_1c_2^2 = 0,$$

65

From (6), we can have two classes of solutions: 66

Case 1. 67

68
$$c_3 \neq$$

68
$$c_3 \neq 0, \ a_0 = -4c_3, \ a_1 = 0, \ a_2 = 0, \ b_0 = 8c_3\alpha, \ b_1 = -8c_3$$
,
69 $b_2 = 0, \ c_1 = 4c_3, \ c_2 = \frac{2c_3}{m}$. (7)

.

Substituting (7) into Eq. (1), we obtain 70

71
$$\psi_{1} = \left(1 + \frac{-1 + i(2\alpha - 2x)}{(x - \alpha)^{2} + \frac{1}{2m}(t - \beta)^{2} + \frac{1}{4}}\right)e^{ix}.$$
 (8)

72

73 Case 2

74 (i)
$$a_0 = 0, a_1 = 0, a_2 = 0, \alpha = \frac{-b_0 - \beta b_2}{b_1}, m = \frac{-b_1^2}{2b_2^2}, b_0 \neq 0, c_1 = -b_1,$$

75
$$m \neq 0, \ c_2 = -\frac{b_1}{2m}, \ c_3 = 0.$$
 (9)

76 (ii)
$$a_0 = 0, a_1 = 0, a_2 = 0, b_0 \neq 0, \alpha = -\frac{\beta b_2}{b_1}, m = -\frac{\beta^2}{2\alpha^2},$$

77
$$c_1 = -b_1, m \neq 0, \ c_2 = -\frac{b_1}{2m}, \ c_3 = 0.$$
 (10)

Substituting (9) and (10) into Eq. (1), we obtain 78

79
$$\psi_{2} = \left(1 + \frac{i(b_{0} + b_{1}x + b_{2}t)}{-b_{1}(x - \frac{-b_{0} - \beta b_{2}}{b_{1}})^{2} + \frac{b_{2}^{2}}{b_{1}}(t - \beta)^{2}}\right)e^{ix},$$
 (11)

80
$$\psi_{3} = \left(1 + \frac{i(b_{0} + b_{1}x + b_{2}t)}{-b_{1}(x + \frac{\beta b_{2}}{b_{1}})^{2} + \frac{b_{2}^{2}}{b_{1}}(t - \beta)^{2}}\right)e^{ix}.$$
 (12)

3. Some properties of rogue waves

82 **3.1 Width of rogue waves**

83 It is well known that the parameter of the nonlinearity have a major impact on the forms of waves. We herein analyze the impact of rogue waves with the varying parameter of the 84 85 nonlinearity. Given by different parameters of the nonlinearity, we draw the corresponding 86 rogue waves and density pictures. It is easy to find that: (1) The nonlinearity parameter m87 has little effect on the height of rogue waves. That is, there is no change the height with 88 different parameters of the nonlinearity. (2) The nonlinearity parameter m has more effect 89 on the width of rogue waves. With the increase of m, the rogue waves becomes wider (in 90 detailed see Figure 1-3).



92 93





(b)

Fig.1. Rogue wave propagations (a) and contour plots (b) for the intensity $\left| \pmb{\psi}_1 \right|^2$ for

95
$$m = 0.005, \alpha = 0,$$



$$100 mtext{ } m = 0$$

| 102 | (<i>a</i>) | (<i>b</i>) |
|-----|---|---|
| 103 | Fig.3. Rogue wave propagations (a) and | contour plots (b) for the intensity $\left \psi_1 \right ^2$ for |
| 104 | $m = 4, \alpha = 0$ | |
| 105 | 3.2 Rogue Waves with a Controllable Cen | ter |

From (8), we find rogue waves will move when α, β are given by different values. When we study the situation before taking α definite values for d of m. The following, we consider wave changes under m taking a fixed value 0.5 and α, β varying. We find the following facts: When α, β are given by different values, the central location of the rogue wave are different, namely, the rogue wave center is movable (see Figure 4-7).

- 112
- 113

117
$$\alpha = 3, \beta = 2.$$

121 Fig.5. Rogue wave propagations (a) and contour plots (b) for the intensity $|\psi_1|^2$ for

122
$$m = 0.5, \alpha = 2, \beta = -2$$

126 Fig.6. Rogue wave propagations (a) and contour plots (b) for the intensity $|\psi_1|^2$ for 127 $m = 0.5 \ \alpha = -2, \ \beta = -2$.

131 Fig.7. Rogue wave propagations (a) and contour plots (b) for the intensity $|\psi_1|^2$ for 132 $m = 4, \alpha = 0.$

133 3.3 Singular rogue waves

According to the analysis in Section 2, when m is a negative value, we find that the denominator value of obtained solutions (11)-(12) can be zero under some positions. So we can obtain some singular rogue waves which are shown as follows.

139 Fig.8. Rogue wave propagations (a) and contour plots (b) for the intensity $|\psi_1|^2$ for

```
140 b_0 = 1, b_1 = 1, b_2 = 1, \beta = 1.
```


143 Fig.9. Rogue wave propagations (a) and contour plots (b) for the intensity $|\psi_1|^2$

144

for $b_0 = 1$, $b_1 = 1$, $b_2 = 1$, $\beta = -1$.

147 Fig.10. Rogue wave propagations (a) and contour plots (b) for the intensity $|\psi_1|^2$ for

148
$$b_0 = -1, b_1 = 3, b_2 = 2, \beta = 2.$$

154 Conclusion

In this paper, we obtain some special rogue waves with a controllable center by a direct method and study the effects of different parameters on rogue waves. We find that the nonlinearity parameter is responsible for the width of rogue waves. In the future, we will study the effects of rogue wave solutions ψ_1 on NLS equations by similarity transformation.

160

161 **References**

- 162 [1] Guo S M,Li Q M,and Wei J S 2013 Physics Letters A 377 2118
- 163 [2] Kharif C, Pelinovsky E, and Slunyaev A, New York: Springer; 2009.
- 164 [3] Akhmediev N, Ankiewicz A, and Taki M 2009 Phys. Lett. A 373 675.
- 165 [4] Sulem C, Sulem P L, Springer-Verlag, New York, 1999.
- 166 [5] Dysthe K B and Trulsen K, 1999 *Phys. Scr. T* 82 48.
- 167 [6] Voronovich V V, Shrira V I, and G. Thomas, J. 2008 Fluid Mech. 604 263.
- 168 [7] Peregrine D H 1983 J. Austral. Math. Soc. Ser. B 25 16
- 169 [8] Akhmediev N, Ankiewicz A and Soto-Crespo J M 2009 Phys. Rev. E 80 026601

- 170 [9] Wei-Ping Zhong, Milivoj R. Beli´ and Tingwen Huang 2013 Phys. Rev. E 87 065201
- 171 [10]M. Golam Hafez, M. A. Kauser, and M. Tahmina Akter 2014 International Journal of
- 172 Scientific Engineering and Technology **3** 848
- 173 [11] Wang X C, He J S and Li Y S, 2011 Phys. 56 631
- 174 [12] Mj-lhus E and Plasma J 1976 Phys. 16 321
- 175 [13] Zhang J F, Jin M Z, He J D, Lou J H, and Dai C Q, 2013 Chin. Phys. B 22 054208
- 176 [14] Tao Y S, He J S, and Porsezian K 2013 Chin. Phys. B 22 074210
- 177 [15] Ma ZY and Ma S H 2012 Chin. Phys. B 21 030507
- 178 [16] Anjan Biswas, A. H. Bhrawy, A. A. Alshaery and E. M. Hilal 2014 Optik 125 4946
- 179 [17] Houria Triki, Sihon Crutcher, Ahmet Yildirim, T. Hayat, Omar. M. Aldossary and Anjan
- 180 Biswas, 2012 Romanian Reports in Physics 64 367
- 181 [18] Laila Girgis, Daniela Milovic, Swapan Konar, Ahmet Yildirim, Hossein Jafari and Anjan
- 182 Biswas 2012 Romanian Reports in Physics 64 663
- 183 [19]Kaisar R. Khan, Mohammad F. Mahmood and Anjan Biswas 2014 IEEE Journal of
- 184 Selected Topics in Quantum Electronics 20 7500309
- 185 [20]Michelle Savescu, A. H. Bhrawy, E. M. Hilal, A. A. Alshaery and Anjan Biswas2014
- 186 Romanian Journal of Physics **59** 582
- 187 [21]Anjan Biswas, Kaisar Khan, Atiqur Rahman, Ahmet Yildirim, T. Hayat and Omar M.
- 188 Aldossary 2012 Journal of Optoelectronics and Advanced Materials 14 571