

Gilbert-Cell Mixer for WiMAX Applications

Frederick Ray I. Gomez

STMicroelectronics, Inc., Calamba City, Laguna, Philippines 4027

ABSTRACT

Differential implementation is becoming highly popular in Radio Frequency Integrated Circuit (RFIC) design, notably for its high immunity to common-mode noises, acceptable rejection of parasitic coupling, and increased dynamic range. One RF front-end building block that is usually designed as a differential circuit is the mixer. This paper presents a design, study, and optimization of a differential mixer, more specifically the Gilbert-cell mixer (also known as double-balanced mixer) implemented on a direct-conversion architecture in a standard 90nm Complementary Metal-Oxide Semiconductor (CMOS) process. Operating frequency is set to 5GHz, which is a typical frequency for Worldwide Interoperability for Microwave Access (WiMAX) receiver. Impedance matching was necessary to design and fully optimize the mixer design. The direct-conversion Gilbert-cell mixer design ultimately achieved conversion gain of 11.463dB and noise figure of 16.529dB, comparable to mixer designs from past research and studies.

Keywords: Gilbert-cell mixer; direct-conversion; conversion gain; noise figure; WiMAX

1. INTRODUCTION

The front-end of a Radio Frequency (RF) wireless receiver is of particular interest to many RF Integrated Circuit (IC) designers and researchers as it attests to be the most critical part in many communication systems and wireless applications like the Bluetooth, Wireless Fidelity (WiFi), and Worldwide Interoperability for Microwave Access (WiMAX). The block diagram of a typical RF or wireless receiver is shown in Fig. 1.




Fig. 1. Block diagram of a typical wireless receiver

Mixer is among the front-end building blocks of an RF receiver. It is also referred to as a converter because it converts RF signals into a lower Intermediate Frequency (IF) by mixing with an offset Local Oscillator (LO). Depending on the RF receiver requirements, mixers must undergo a careful design process since complex tradeoffs exist among different performance parameters. For this paper, the objective is then to design and optimize a direct-conversion Gilbert-cell (or double-balanced) mixer implemented in a standard 90nm Complementary Metal-Oxide Semiconductor (CMOS) process. Operating frequency is set to 5GHz, which is a typical frequency for an RF receiver particularly the WiMAX receiver.

2. LITERATURE REVIEW

Receivers can be categorized as high-IF, low-IF, and zero-IF or direct-conversion based on the resulting IF signal they operate. For the direct-conversion receiver, IF is designed to be centered at DC (direct current) or zero frequency. This indicates that the LO frequency is equal to the input RF frequency. With zero-IF, image signal is avoided and the analog filtering problem can be easily handled. Moreover, the desired signal is translated directly to the baseband, allowing Analog-to-Digital Converter (ADC) and Digital Signal Processing (DSP) circuits to perform modulation and other auxiliary functions [1]. This eliminates the need for highly complex filters since channel selection only requires a Low-Pass Filter (LPF) as shown in Fig. 2. Smaller and cheaper receivers with low power consumption could be realized for various wireless applications such as Bluetooth, WiFi, and WiMAX. Many of the implemented receivers in WiMAX [2] [3] use the zero-IF architecture since the LPFs make sure that the closely-spaced carrier signals do not cause interference with each other.




Fig. 2. Direct-conversion or zero-IF receiver

Designing a mixer must take into consideration the tradeoffs among the performance parameters. As previously mentioned, a careful study of these important parameters must be done in order to design a fully-functional and optimized mixer. A mixer's efficiency on frequency conversion from RF to IF is characterized by conversion gain (CG) or loss, expressed in Eq. (1) and (2). CG is the ratio of the desired IF output to the value of the RF input, and may be expressed in voltage or power. In cases when conversion gain is less than unity or 0dB, it is appropriately termed as a conversion loss.

$$CG_{voltage} = 20 \log \frac{V_{IF}}{V_{RF}} \quad \text{Eq. (1)}$$

$$CG_{power} = 20 \log \frac{P_{IF}}{P_{RF}} \quad \text{Eq. (2)}$$

V_{IF} and V_{RF} are the root mean square (RMS) voltages of the IF and RF signals, respectively, while P_{IF} and P_{RF} are the equivalent power of the IF and RF signals, respectively. Conversion gain is preferred over conversion loss because amplification along with frequency translation. Nonetheless, it should be noted that conversion gain directly affects

the noise figure and linearity of the overall receiver. Hence, design tradeoffs concerning these parameters are inevitable.

Noise figure (NF) is another important parameter of the mixer. It is a measure of the amount of signal-to-noise-ratio (SNR) degradation introduced by the mixer as seen at the output. Eq. (3) shows the relation between the SNR at the input port (SNR_{IN}) and the SNR at the output port (SNR_{OUT}) of the mixer.

$$NF = 10 \log \left(\frac{SNR_{IN}}{SNR_{OUT}} \right) \quad \text{Eq. (3)}$$

Noise figures of mixers tend to be higher than amplifiers (i.e. low-noise amplifiers, power amplifiers) because of the noise contribution of preceding building blocks and the noise generated from stray and nearby frequencies (apart from input RF signal) that can mix down to the IF. This considerable noise in mixers is the main reason why Low-Noise Amplifiers (LNA) are used in the front-end, before the mixer [4].

A popular solution for the mixer is based on the double-balanced topology, with the schematic shown in Fig. 3. Double-balanced mixer is also commonly known as Gilbert-cell mixer. It operates with differential LO and RF inputs. In this topology, LO products are prevented from getting to the output by combining two single-balanced mixers. As illustrated in Fig. 3, the two single-balanced mixers are connected in anti-parallel as far as the LO is concerned, but in parallel for the RF signal. Thus, the LO terms sum to zero in the output, whereas the converted RF signal is doubled in the output [4] [5]. This is most desirable for high port-to-port isolation and spurious output rejection applications.




Fig. 3. Gilbert-cell mixer or double-balanced mixer configuration

As earlier mentioned, the goal of the paper is then to design and optimize a direct-conversion Gilbert-cell mixer implemented in a standard 90nm CMOS process, operating at frequency of 5GHz which is a typical frequency for a WiMAX receiver. The target specifications of the figures of merit are based on the performance comparison in terms of conversion gain and noise figure of past researches on direct-conversion active mixer topologies given in Table 1.

Fig. 4. Schematic design of Gilbert-cell mixer

One way to increase the performance of the mixer in terms of conversion gain and noise figure is to apply impedance matching in the circuit. Input impedances Z_{11} and Z_{22} can be obtained using S-Parameter (SP) analysis which is swept from frequency $f_1 = 700\text{MHz}$ to $f_2 = 6\text{GHz}$. Actual inductor and capacitor values at frequency $f = 5\text{GHz}$ can be computed from the L-network reactances.

To supply differential LO input to the mixer, a port PORT2 with a matching resistor (set to 50Ω) is used which is then fed into an ideal passive balun to convert the single-ended signal into differential. For the differential RF input of the mixer, same setup as the LO is used with PORT1. To use the differential output for measurements, matching the IF output port PORT3 to the output impedance of the mixer is necessary. PORT1 is set to DC source type with Periodic AC Magnitude (pacmag) set to 1. PORT3, which is the IF port, is set also to DC source type. The only large signal is from PORT2 which is a sine wave with $f_{LO} = 5\text{GHz}$ and $P_{LO} = 0\text{dBm}$.

For the impedance matching, the input matching network is applied before the differential RF input of the mixer instead of placing it before the balun. Impedance matching is essential in RF circuit design to provide maximum possible power transfer between the source or the generator and the load [1] [10]. This will result to an adjustment on the value of L_1 , which will decrease, since the balun circuit has self-inductance. The adjusted value of L_1 can be determined using the SP analysis swept from $f_1 = 700\text{MHz}$ to $f_2 = 6\text{GHz}$. Moreover, inductors with small inductances are more realizable in actual designs than their larger counterparts. The final values of the L-matching network are summarized in Table 2.

Table 2. Performance comparison of mixer designs of past researches

L and C	Value
L_1	12.7 nH
C_1	1.116 pF
L_2	1.329 nH
C_2	267.127 fF

Software design tools namely Analysis and Simulation of Spiral Inductors and Transformers for ICs (ASITIC) [11] [12] and Integrated Spiral Inductor Calculator (SpiralCalc) [13] [14] are used for the design of the inductors. Both tools are available for academic and non-commercial purposes. Table 3 shows the design parameters obtained for the design of the spiral inductors using ASITIC while Table 4 shows that of using SpiralCalc.

Table 3. Inductor design using ASITIC

Design Parameters	Inductors	
	L_1	L_2
Desired L	12.7 nH	1.329 nH
No. of sides	4	8
Length, D	300 μm	190 μm
Metal width, W	10.886 μm	10.902 μm
Spacing, S	1	1
No. of turns, N	4.25	2.5
Metal layer	7	7
Inductance, L	12.711 nH	1.329 nH

Q-factor, Q	2.322	5.694
-------------	-------	-------

Table 4. Inductor design using SpiralCalc

Design Parameters	Inductors	
	L_1	L_2
Desired L	12.7 nH	1.329 nH
No. of sides	4	8
Length, D	300 μm	190 μm
Metal width, W	11.2 μm	10 μm
Spacing, S	1	1
No. of turns, N	6	2
Inductance, L:		
Modified Wheeler	12.885 μm	1.326 μm
Current Sheet	12.739 μm	1.326 μm
Monomial Fit	12.624 μm	1.394 μm

In ASITIC, the spiral inductors are designed such that desired inductances are achieved and the Q-factors are optimized with eddy-current option enabled to include the effects of substrate induced eddy current losses. Inductor L_1 have smaller Q-factor than L_2 because of its high inductance value. For the inductor design using SpiralCalc, same parameter values from the ASITIC parameters are used except for the metal width and the number of turns of the spiral inductor. These parameters are tweaked such that the desired inductances are achieved for the inductors.

The n2port from the analogLib library is used as a model block for all the ASITIC inductors. Touchstone format of S-parameter file is used as file input of the n2port component since the actual S-parameters using ASITIC are given in touchstone format. The figures of merit such as conversion gain and noise figure are determined using SpectreRF in the Analog Design Environment.

4. RESULTS AND ANALYSIS

A mixer's frequency converting action is characterized by conversion gain or loss. Voltage conversion gain is the ratio of the RMS voltages of the IF and RF signals, earlier given in Eq. (1). The variations of conversion gain with the power of LO signal (P_{LO}) can be measured using swept Periodic Steady-State (PSS) analysis with Periodic AC (PAC) analysis. The PAC analysis will then compute the voltage conversion gain in dB20 of the whole circuit with PORT3 as the output port (with output harmonic of 0, which is 5GHz) and PORT1 as the input port (with input harmonic of -1, which is 0GHz). Setting the input port to RF+ port, which is located after the balun circuit, will compute the voltage conversion gain of the mixer only. Simulation plots of the conversion gain swept from $P_{LO} = -10\text{dBm}$ to $P_{LO} = 30\text{dBm}$ are shown in Fig. 5-7.




Fig. 5. Conversion gain (in dB) vs. P_{LO} (w/o matching)




Fig. 6. Conversion gain (in dB) vs. P_{LO} (with ideal L)




Fig. 7. Conversion gain (in dB) vs. P_{Lo} (using ASITIC L)

Based on the conversion gain simulation plots, input and output impedance matching contribute to better performance. Furthermore, using ideal inductors for impedance matching produced better performance as compared to using non-ideal ASITIC inductors through the n2port. It can be observed from the simulation plots that the conversion gain of the mixer only is higher than the conversion gain of the whole circuit consisting of the mixer and the balun. This is because the balun in the circuit, which is a passive balun, has insertion loss and thus incapable of producing gain. When a passive balun is cascaded with another block, for this case the mixer, the overall gain is degraded.

For the noise figure, Periodic Noise (Pnoise) analysis with PSS analysis is used. Alternatively, Periodic S-Parameters (PSP) analysis with PSS analysis can also be used to determine the noise figure of the circuit. Noise figure from a sweep range of -10dBm to 30dBm can now be determined and plotted using these analyses. The resulting plots are shown in Fig. 8-9.




Fig. 8. Noise figure (in dB) vs. P_{LO} of (Pnoise analysis)




Fig. 9. Noise figure (in dB) vs. P_{LO} of (PSP analysis).

Input and output impedance matching also contribute to better noise performance of the circuit, as indicated in Fig. 8-9. It can be observed that using ideal inductors for impedance matching produced lower noise figure as compared to using non-ideal ASITIC inductors through the n2port model. The model block n2port introduces noise to the system, hence, adding to the total noise figure of the circuit.

Table 5 summarizes the simulation results for conversion gain and noise figure at P_{LO} = 0dBm.

238
239
240

Table 5. Simulation results, at $P_{LO} = 0\text{dBm}$

Figures of Merit	Value
CG (mixer+balun) [w/o matching]	-17.431dB
CG (mixer) [w/o matching]	-11.410dB
CG (mixer+balun) [ideal L]	5.443dB
CG (mixer) [ideal L]	11.463dB
CG (mixer+balun) [ASITIC L]	-10.966dB
CG (mixer) [ASITIC L]	-4.946dB
<i>Pnoise NF</i> [w/o matching]	125.355dB
<i>Pnoise NF</i> [ideal L]	16.529dB
<i>Pnoise NF</i> [ASITIC L]	33.713dB
<i>PSP NF</i> [w/o matching]	8.127dB
<i>PSP NF</i> [ideal L]	7.136dB
<i>PSP NF</i> [ASITIC L]	21.437dB

241

242 It is evident that input and output impedance matching contribute to better performance
243 based on the figures of merit presented for the Gilbert-cell mixer design. It is observed that
244 the conversion gain of the mixer is higher than the conversion gain of the circuit consisting of
245 the mixer and the balun. The reason is that the conversion gain performance at the system-
246 level perspective is greatly influenced by the performance of the initial or preceding blocks,
247 for this case the passive balun. Hence, it is of high importance to consider the contribution of
248 the input or previous circuit (and as well as the output or succeeding circuit) in fully designing
249 and optimizing the mixer.

250

251

252 **5. CONCLUSIONS AND RECOMMENDATIONS**

253

254 A design of Gilbert-cell mixer with direct-conversion architecture was implemented and
255 optimized on this paper. Conversion gain and noise figure were determined to gauge the
256 performance of the mixer design. These performance parameters can still be enhanced or
257 optimized by applying impedance matching in the circuit. The effect of the passive balun in
258 the mixer design was also observed, resulting to the decrease in the conversion gain of the
259 mixer. Nevertheless, the direct-conversion Gilbert-cell mixer design achieved conversion
260 gain of 11.463dB and noise figure of 16.529dB using Pnoise analysis at 5GHz, comparable
261 to mixer designs from past studies and research.

262

263 For future studies, active baluns could be used in place of passive baluns for monolithic
264 implementation. Active baluns are capable of producing gain and if cascaded in a double-
265 balanced mixer to supply the differential RF and LO inputs, the overall performance of the
266 mixer can be improved [6]. Although active baluns are unidirectional converters, they can be
267 used for their large bandwidth, which is beyond from what non-ideal passive baluns can
268 offer.

269

270

271 **ACKNOWLEDGEMENTS**

272

273 The author would like to extend appreciation to Prof. Maria Theresa De Leon, Ph.D. and
274 Prof. John Richard E. Hizon, Ph.D. of Microelectronics and Microprocessors Laboratory at
275 the University of the Philippines for the technical support during the course of the study. The

author is greatly thankful to the STMicroelectronics Calamba NPI Team and the Management Team for the utmost support.

REFERENCES

1. Razavi B. RF microelectronics. 2nd ed. Upper Saddle River, New Jersey, USA: Prentice Hall Press; 2011.
2. Zhou Y, Yoong CP, Weng LS, Khoi YJ, Wah MCY, Moy KAC, Fatt DWT. A 5 GHz dual-mode WiMAX/WLAN direct-conversion receiver. IEEE International Symposium on Circuits and Systems; May 2006.
3. Atallah JG, Rodriguez S, Zeng LR, Ismail M. A direct conversion WiMAX RF receiver front-end in CMOS technology. International Symposium on Signals, Circuits and Systems, vol. 1; July 2007.
4. Lee T. The design of CMOS radio-frequency integrated circuits. 2nd ed. Cambridge: Cambridge University Press; 2003.
5. Valtti M, Koivisto T, Tiiliharju E. Comparison of active and passive mixers. 18th European Conference on Circuit Theory and Design, pp. 890-893; August 2007.
6. Gomez FR, De Leon MT, Roque CR. Active balun circuits for WiMAX receiver front-end. TENCON 2010 – IEEE Region 10 Conference, pp. 1156-1161; November 2010.
7. Tikka T, Ryyanen J, Hotti M, Halonen K. Design of a high linearity mixer for direct-conversion base-station receiver. IEEE International Symposium on Circuits and Systems; May 2006.
8. Hamed KW, Freundorfer AP, Antar YMM. A monolithic double-balanced direct conversion mixer with an integrated wideband passive balun. IEEE Journal of Solid-State Circuits, vol. 40, no. 3, pp. 622-629; March 2005.
9. Park J, Lee CH, Kim BS, Laskar J. Design and analysis of low flicker-noise CMOS mixers for direct-conversion receivers. IEEE Transactions on Microwave Theory and Techniques, vol. 54, no. 12; December 2006.
10. Gomez FR. Design of impedance matching networks for RF applications. Asian Journal of Engineering and Technology, vol. 6, no. 4; September 2018.
11. Meyer RG, Niknejad AM. ASITIC for Windows NT/2000. Research in RFIC Design. Available: http://rfic.eecs.berkeley.edu/~niknejad/Asitic/grackle/cygwin_info.html.
12. Niknejad AM, Meyer RG. Analysis and optimization of monolithic inductors and transformers for RF ICs. IEEE Custom Integrated Circuits Conference, Santa Clara, CA, pp. 375-378; May 1997.
13. Stanford Microwave Integrated Circuits Laboratory. Integrated Spiral Inductor Calculator. Available: <http://www-smirc.stanford.edu/spiralCalc.html>.

327 14. Mohan SS, del Mar Hershenson M, Boyd SP, Lee TH. Simple accurate expressions for
328 planar spiral inductances. IEEE Journal of Solid-State Circuits, vol. 34, issue 10, pp. 1419-
329 1424; October 1999.
330